



# D1000 Series

## Digital Cordless Phones



***Highly stylised cordless phone system for the design conscious homeowner***

***Ultra slim handset***

***Backlit display and illuminated glow-ring event indicator***

### Key Features

- 100 number phone book
- Large "easy-read" backlit display
- Handsfree speakerphone
- Room monitor
- Remote access to messages
- Message indicator for answer machine

### Pack Contents

- Standard and answering machine variants in various handset multiples.
- Pack contents include handset(s), combined base-unit/charger, additional handset charger for multiple handset variants, telephone line-cord (plus local adapters where appropriate), AC adapters, wall-mounting bracket(s) and user instructions.
- D1001, D1002 digital cordless phones
- D1011, D1012, D1013 digital cordless phones with answer machines

**Specification Sheet - Advanced information and subject to confirmation**



D1000



D1010



Additional handset/charger

**FEATURES**

|  | <b>D1000</b><br>4-line Full dot-matrix LCD<br>Digital cordless phone                       | <b>D1010</b><br>4-line Full dot-matrix LCD<br>Digital cordless phone +<br>Answering Machine                                    |
|--|--|--|
| <b>Display and Aesthetics</b>                          |  |  |
| Display  | Black and White; 2-line alpha-numeric dot matrix x 12 plus 2 line icons                    |  |
| LEDs / Indicators                                      | Handset:<br>Events / messages (1 glow-ring LED);<br>Base:<br>Charging (1 LED),             | Handset:<br>Events / TAM messages (1 glow-ring LED);<br>Base:<br>In use (1 LED)<br>Charging (1 LED),<br>Messages (1 large LED) |
| Display Backlight                                      | Yes (Amber)  |  |
| <b>Character Sets / Text</b>                           |  |  |
| Word wrap  | YES  |  |
| <b>General Features</b>                                |  |  |
| GAP Compatibility                                      | YES  |  |
| Multi-base / Handset                                   | 4 Base / 5 Handsets  |  |
| Base Station / Handset System Security (PIN code)      | Up to 4 digits, (default code 0000)  |  |
| Dialling Mode  | Tone / Standard Pulse. (Use * key to change the dial mode from Pulse to tone temporarily). |  |
| Paging From base to handset(s)                         | YES  |  |
| "3 way conferencing (2 internal with 1 external)"      | YES  |  |
| "3 way conferencing "plus simultaneous intercom"       | YES  |  |
| Auto-talk / Standby                                    | YES, user can disable Auto-talk  |  |
| Recall / Flash   | Timed Break  |  |
| Dialling Pause   | YES  |  |
| Pre-dialling Facility                                  | YES  |  |
| Out-of-range Warning                                   | Standby : visual; In Call : audible and visual   |  |
| Restore to Default Settings                            | YES  |  |
| Alarm  | YES  |  |
| Low Battery Warning                                    | Standby : visual; In Call : audible and visual   |  |
| Call Timer   | YES  |  |
| Handset Power On/Off                                   | YES  |  |
| Microphone Mute Facility                               | YES  |  |
| Last Number Redial                                     | 10 entries - Delete All / Selective Delete   |  |
| Ability To Name Handsets                               | YES  |  |
| Keypad Lock  | YES  |  |
| Call Transfer Between Handsets                         | YES  |  |
| Intercom Between Handsets                              | YES  |  |
| Low Radiation (Eco mode)                               | YES  |  |
| Room monitor   | YES  |  |
| Easy Call  | YES  |  |
| <b>Sounds / Audio</b>                                  |  |  |
| Hands-free speakerphone                                | YES  |  |
| Ringer Melodies  | 10 - 8ch Polyphonic  |  |
| Ringer Volume Control                                  | Handset: 5 Levels + OFF;   |  |
| Handset Receiver Volume Control                        | 5 Levels (available in-call and during message playback)                                   |  |
| <b>Phonebook Features</b>                              |  |  |
| Phonebook  | 100 names & numbers, available in idle/during talk Stored in handset                       |  |
| Phonebook "instant copy" between handsets              | YES  |  |
| Delete all Phonebook entries                           | YES  |  |
| Save Number in pre-dial mode                           | YES  |  |
| Copy Caller ID entry to phonebook                      | YES  |  |
| Copy Redial number to phonebook                        | YES  |  |
| <b>Caller ID Features</b>                              |  |  |
| Caller ID Mode   | FSK/DTMF   |  |
| Caller ID Type   | Type 1 and 2   |  |
| Calls List   | 50, dynamic allocation between Received and Missed   |  |
| Both name & number displayed during incoming caller ID | YES  |  |
| Calls List Includes Time / Date of Call                | YES  |  |
|  | Taken from calendar if network does not supply time/date                                   |  |

## Specification Sheet

### FEATURES

|  | D1000<br>4-line Full dot-matrix LCD<br>CID | D1010<br>4-line Full dot-matrix LCD<br>CID + Answering Machine   |
|--|--|--|
| <b>Answering Machine Features</b>                |  |  |
| Voice Prompts                                    |  | YES (Depending on region, voice prompts available in English, French, German, Italian, Russian, Spanish)   |
| Outgoing Message                                 |  | 1 x Answer & Record, 1 x Answer only (max recording time 3 minutes for each)   |
| Pre-recorded Outgoing message (OGM)              |  | YES (Depending on region, pre-recorded OGM available in Bulgarian, Croatian, Czech, Danish, Dutch, English, Finnish, French, German, Greek, Hungarian, Italian, Norwegian, Polish, Portuguese, Romanian, Russian, Serbian, Slovakian, Spanish, Turkish, Ukrainian) |
| "Total Recording Time (excluding voice prompts)" |  | 12 Minutes   |
| Incoming Messages                                |  | Each ICM : Max 3 minutes;<br>Maximum number of messages : 59   |
| Call Screening                                   |  | YES  |
| Call Intercept                                   |  | YES  |
| Memo Message                                     |  | YES from Handset   |
| Message Indicator                                |  | Yes - Large LED  |
| Message Playback Features                        |  | Skip Back, Skip Forwards, Delete, Stop   |
| Message Full Indication                          |  | YES  |
| Private Playback Via Handset                     |  | YES  |
| Ring Delay Selector                              |  | 2-9, Toll Saver  |
| Remote Access ID                                 |  | 4digit   |
| Remote Access Options                            |  | Messages: Play, Delete (selective), Skip back, skip forwards;<br>General: Switch on/off  |
| <b>Technical Characteristics</b>                 |  |  |
| Last Number Redial Memory Length                 |  | 24 digits  |
| Phonebook Name Length                            |  | 12 characters  |
| Memory Number Length                             |  | 24 Digits  |
| Handset Name Length                              |  | 10 characters  |
| Battery Type                                     |  | NiMH 2 cell  |
| Standby Time                                     |  | Up to 100 hours  |
| Talk Time  |  | Up to 10 hours   |
| Range  |  | Up to 300m (outdoor), up to 50m (indoor)   |



**Specification Sheet - Advanced information and subject to confirmation**

| Codes & part numbers |           |               |               |   |
|----------------------|-----------|---------------|---------------|---|
| Sales Model          | S/T       | Description   | EAN           | Target Countries  |
| S11SCB0DA0AA         | SCUX9040A | DECT D1001 UK | 5031753005795 | UK  |
| S11SCA0DA0AA         | SCUX9000A | DECT D1001 WE | 5031753005399 | France, Germany, Italy, Spain, Netherlands, Switzerland, Austria            |
| S11SCA0DB0AA         | SCUX9001A | DECT D1001 EU | 5031753005405 | Turkey, Czech Republic, Hungary, Slovakia, Greece, Croatia, Poland, Romania |
| S11SCE0DA0AA         | SCUX9002A | DECT D1001 RU | 5031753005412 | Russia, Ukraine, Bulgaria, Serbia   |
| S11SCA0DC0AA         | SCUX9003A | DECT D1001 NX | 5031753005429 | Norway, Sweden, Denmark, Finland, Portugal                                  |
| S11SCG0DA0AA         | SCUX9041A | DECT D1001 SA | 5031753005801 | SA  |
| S12SCB0DA0AA         | SCUX9004A | DECT D1002 UK | 5031753005436 | UK  |
| S12SCA0DA0AA         | SCUX9005A | DECT D1002 WE | 5031753005443 | France, Germany, Italy, Spain, Netherlands, Switzerland, Austria            |
| S12SCA0DB0AA         | SCUX9006A | DECT D1002 EU | 5031753005450 | Turkey, Czech Republic, Hungary, Slovakia, Greece, Croatia, Poland, Romania |
| S12SCE0DA0AA         | SCUX9007A | DECT D1002 RU | 5031753005467 | Russia, Ukraine, Bulgaria, Serbia   |
| S12SCA0DC0AA         | SCUX9008A | DECT D1002 NX | 5031753005474 | Norway, Sweden, Denmark, Finland, Portugal                                  |
| S12SCG0DA0AA         | SCUX9042A | DECT D1002 SA | 5031753005818 | SA  |
| S11SCB0DA1AA         | SCUX9009A | DECT D1011 UK | 5031753005481 | UK  |
| S11SCA0DA1AA         | SCUX9010A | DECT D1011 WE | 5031753005498 | France, Germany, Italy, Spain, Netherlands, Switzerland, Austria            |
| S11SCA0DB1AA         | SCUX9011A | DECT D1011 EU | 5031753005504 | Turkey, Czech Republic, Hungary, Slovakia, Greece, Croatia, Poland, Romania |
| S11SCE0DA1AA         | SCUX9012A | DECT D1011 RU | 5031753005511 | Russia, Ukraine, Bulgaria, Serbia   |
| S11SCA0DC1AA         | SCUX9013A | DECT D1011 NX | 5031753005528 | Norway, Sweden, Denmark, Finland, Portugal                                  |
| S12SCB0DA1AA         | SCUX9014A | DECT D1012 UK | 5031753005535 | UK  |
| S12SCA0DA1AA         | SCUX9032A | DECT D1012 WE | 5031753005719 | France, Germany, Italy, Spain, Netherlands, Switzerland, Austria            |
| S12SCA0DB1AA         | SCUX9033A | DECT D1012 EU | 5031753005726 | Turkey, Czech Republic, Hungary, Slovakia, Greece, Croatia, Poland, Romania |
| S12SCE0DA1AA         | SCUX9034A | DECT D1012 RU | 5031753005733 | Russia, Ukraine, Bulgaria, Serbia   |
| S12SCA0DC1AA         | SCUX9035A | DECT D1012 NX | 5031753005740 | Norway, Sweden, Denmark, Finland, Portugal                                  |
| S13SCB0DA1AA         | SCUX9015A | DECT D1013 UK | 5031753005542 | UK  |
| S13SCA0DA1AA         | SCUX9043A | DECT D1013 WE | 5031753005825 | France, Germany, Italy, Spain, Netherlands, Switzerland, Austria            |

For more information please contact your local Motorola Authorised Dealer or Distributor

